

Product summary


Cascadable multiswitch, passive terrestrial, self-powered

Brief description

9in/9out+6 compact cascadable multiswitch for distribution terrestrial and satellite signals from 2 satellite positions (8 polarities) to 6 users.

The multiswitch is DC supplied from connected satellite receivers, DC2.1 socket for external power is connected to all satellite trunk lines.

DC pass is provided through the TERR line.

**Technical data**

Parameter	Condition	Value
Frequency range	Sat. trunks	950-2150 MHz
	Terr. trunk	40-862 MHz
	User outputs	40-2150 MHz
Control		13/18 V + 0/22 kHz + DiSEqC
Insertion loss - user outputs	Sat.	5 dB avg
	Terr	22 dB avg
Insertion loss - trunk outputs	Sat.	2.5 dB avg
	Terr	4 dB avg
Sat. inputs isolation	At user outputs	20 dB min
	At trunk outputs	25 dB min
Maximum input level*	Sat./Terr.	105/105 dBμV
Maximum user output level*	Sat./Terr	100/70 dBμV
Current consumption	Per user output	100 mA (18 V)
Dimensions (w,d,h)		18.6 x 14.6 x 5.1 cm
Temperature range		-25 ~ +60 °C
Weight		1.005 kg

Postal address: EMP-Centauri s.r.o. 5. května 690 339 01 Klatovy Czech Republic

Management: Tel.: +420 376 323 813 Tel.: +420 603 497 419 E-mail: info@emp-centauri.cz

Sales department: Tel.: +420 376 323 813 Tel.: +420 603 497 419 Tel.: +420 776 619 976 (EN) Tel.: +420 778 066 654 (CZ) E-mail: sales@emp-centauri.cz

Purchase department: E-mail: purchase@emp-centauri.cz

Technical support: Tel.: +420 376 323 853 (during workhours) Hotline: +420 603 497 419 (available anytime) E-mail: support@emp-centauri.cz Skype ID : **live::cid.624e3941fb5334d9**