

Product summary

FBT Fiber tap, SC/APC

Brief description

Fiber tap FBT-A-1x2-10:90, 2 outputs, single mode, connectors SC/APC, through loss approx. 1 dB, tap loss approx. 12 dB

**Technical data**

Parameter	Value
Operation wavelengths	1270-1610 nm
Dimensions (L×W×H)	130×100×25mm

Postal address: EMP-Centauri s.r.o. 5. května 690 339 01 Klatovy Czech Republic

Management: Tel.: +420 376 323 813 Tel.: +420 603 497 419 E-mail: info@emp-centauri.cz

Sales department: Tel.: +420 376 323 813 Tel.: +420 603 497 419 Tel.: +420 776 619 976 (EN) Tel.: +420 778 066 654 (CZ) E-mail: sales@emp-centauri.cz

Purchase department: E-mail: purchase@emp-centauri.cz

Technical support: Tel.: +420 376 323 853 (during workhours) Hotline: +420 603 497 419 (available anytime) E-mail: support@emp-centauri.cz Skype ID : **live::cid.624e3941fb5334d9**